

# **DVR4-Net-PLUS™**

## 4 Channel Digital Video Recorder

for Network & Web Monitoring with USB



- Monitor & record up to 4 cameras simulataneously
- Connect & view your cameras over a Local Area Connection (LAN) or via remote connection across the Internet\*
- $\bullet$  Set & forget operation with programable motion detection & schedule recording
- Easy installation, use with any TV monitor & security cameras
- Variable compression recording for high quality playback or increased storage capacity
- USB plug for connection to PC for video backup
- Maximum 400 GB IDE HDD (Not included)
- \* Must have suitable broadband Internet connection

Use the remote control to operate your PTZ camera





We recommend using high quality USB Thumb Drives Only \*

## **DVR4-Net-PLUS™** 4 Channel Digital Video Recorder

for Network & Web Monitoring with USB

The Swann DVR4-Net-Plus is the next generation of DIY security safety monitoring. Featuring four standard composite video inputs and 2 video outputs. It is the ideal CCTV system for small retail stores, homes or as a replacement for old fashioned time lapse recorders. Integrated motion activated recording also makes it ideal for covert observation systems. Control of the unit is via the front panel controls and on-screen display menu. Video recording is activated manually via alarm-inputs or automatically via built-in motion detection.

#### **Home**







**Business** 




**Backyard** 



### Technical Specification

Model	Full Function
Motion Trigger Recording	Yes
Record Mode	Manual / Sensor / Timer / Motion Detection
Audio Input	4 audio inputs (RCA)
Audio Output	I audio inputs (RCA)
Alarm Input	NO or NC, 4CH
Alarm Output	NO or NC, ICH
Video Format	PAL/CCIR (AUS, NZ, UK) OR NTSC/EIA (USA)
Hard Disk Storage	Supported up to 400GB HDD
Compression Format	Modified Mjpeg
Camera Input Signal	Composite video signal 1 Vp-p 75Ω BNC, 4 Channels
Primary Monitor Output	Composite video signal 1 Vp-p 75Ω BNC
Secondary Monitor Output	Composite video signal 1 Vp-p 75Ω BNC
Additional Monitor Output	Super Video: S-Video, PS/2 x I
Display Resolution	720 * 576 (PAL), or 720 * 480 (NTSC)
Record Resolution	720 * 288 or 360 * 288 (PAL), 720 * 240 or 360 * 240 (NTSC)
Display Frame Rate	400 FPS (PAL), 480FPS (NTSC)
Record Frame Rate	50 FPS or 100 FPS (PAL), 60 FPS or 120 FPS (NTSC)
Picture In Picture	Yes (Multi PIP)
Key Lock	Yes
Video Adjustable	Hue/ Color/ Contrast / Brightness Adjustable
Simplex/Duplex/Triplex Operation	Triplex
Time Display Format	YY/MM/DD, DD/MM/YY, MM/DD/YY, OFF
Network Interface	RJ45 (LAN, INTERNET)
PTZ control	YES
Communication Port	RS485
Remote Controller	Yes
Backup	USB, CDRW
USB	USB 1.1
Operating Temperature	41°F ~ 122 °F / 5°C ~ 50 °C
Dimensions H x W x D	3" x 17" x 13" / 67 x 430 x 320mm
Power Supply	I2V

Picture used on packaging are for illustration purposes only.



### **Package Contents:**

- DVR4-Net-PLUS
- Hard Drive Tray & Key
- Power Adapter • Power Cable
- Remote Viewing Software (PC Only)
- 6 x BNC to RCA Adapters
- Remote Control
- Requires 2 AA batteries (not included)
- Instructional Manual (Manual only available in English)

#### **FRONT**



#### **BACK**

















www.swannsecurity.com